

II. CLAIM AMENDMENTS

1. (Currently Amended) An arrangement for matching impedance of an antenna against an effect of conductive objects placed near the antenna on the antenna impedance in a radio apparatus having at least two operating bands, the arrangement comprising a radio-frequency power amplifier, means for measuring a reflected field, a matching circuit and a control unit for controlling the matching circuit on the basis of the strength of the reflected field, wherein said means for measuring the reflected field comprises an element which separates the reflected field to a separate path and which is connected to an output of the power amplifier in transmission path of a signal to be transmitted, and said control unit comprises means for controlling the matching circuit also on the basis of information, which of said frequency bands is currently in use.
2. (Original) An arrangement according to claim 1, said element separating the reflected field to a separate path is a circulator arranged to direct the reflected field to the control unit and, furthermore, to prevent the reflected field from propagating to the power amplifier.
3. (Previously Presented) An arrangement according to claim 1, said control unit comprising a detector of the strength of a radio-frequency alternating field and a control logic in order to change the impedance of the matching circuit.

4. (Previously Amended) An arrangement according to claim 1, said matching circuit comprising at least one part having a reactance of which can be controlled electrically.
5. (Cancelled)
6. (Previously Presented) An arrangement according to claim 1, said control unit comprising means for controlling the matching circuit also on the basis of output power information of the power amplifier.
7. (Previously Amended) An arrangement according to claim 4, said at least one part having a reactance of which can be controlled electrically, comprising at least one MEMS capacitor.
8. (Currently Amended) A mobile station comprising an antenna, an antenna matching circuit for matching the antenna against an effect of conductive objects placed near the antenna on the antenna impedance, a power amplifier feeding the antenna, means for measuring a field reflected from the antenna towards the power amplifier, means for attenuating the reflected field, and a control unit for controlling said matching circuit on the basis of the strength of the reflected field, wherein said means for measuring the reflected field comprises an element which separates the reflected field to a separate path and which at the same time constitutes said means for attenuating the reflected field.